



Description

The SA477H is an integrated Hall sensor with H-Bridged output driver designed for brushless DC motor applications. The device includes an on-chip Hall sensor for magnetic sensing, an amplifier that amplifies the Hall voltage, a comparator to provide switching hysteresis for noise rejection, a bi-directional driver for sinking and driving large current load.

Placing the device in a variable magnetic field, if the magnetic flux density is larger than threshold BOP, the DO is turned to sink and DOB is turned to drive. This output state is held until the magnetic flux density reverses and falls below BRP, then causes DO to be turned to drive and DOB turned to sink.

Features

- Operating Voltage: 3.5V to 28V
- Output Current: 350mA
- On-Chip High sensitivity Hall-effect Sensor
- H-Bridge Output Drivers for Single Coil
- Built-in Reverse Protection Diode
- Thermal Shutdown Protection
- Low Output Switching Current Noise
- -40°C to 125°COperating Temperature
- SIP-4L Packages

Application

• Fan Driver

SA477H Package & Simplified Application





Typical Fan Driver

Device Information

| Part No. | Package | Quantity | Operation Temp. |
|----------|---------|----------|-----------------|
| SA477H | SIP4 | 1000 | -40~125°C |



Pin Descriptions



| NO. | NAME | TYPE | DESCRIPTION |
|---------|------|------|---------------------------------------------------------------|
| 1 | | | Power Supply for H-Bridge, Connection 1uF or bigger capacitor |
| I VDD F | | I | between VDD and GND in high voltage application |
| 2 | DO | I | Output 1 |
| 3 | DOB | I | Output 2 |
| 4 | GND | Р | Ground |



Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)

| | | MIN | MAX | UNIT |
|-----------------------------------|------------------|------|-----------|-------|
| Power supply voltage | VDD | -0.3 | 30.0 | V |
| Continuous phase node pin voltage | DO, DOB | -0.3 | VDD | V |
| Magnetic Flux Density | В | | Unlimited | Gauss |
| | Continuous | | 350* | mA |
| Output current (SIP4) | Hold | | 400 | mA |
| | Peak (Start-Up) | | 800 | mA |
| Operating junction temperature, | TJ | -40 | 150 | °C |
| Storage temperature, | T _{stg} | -65 | 150 | °C |
| Thermal Impedance (SIP4) | θ _{JA} | | 227 | °C/W |

Notes: * Using 25mm² FR4 Signal layer PCB (1 oz) under VM=9.0V test.

Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

| | | MIN | MAX | UNIT |
|------------------------|----------------|-----|-------|------|
| Power supply voltage | VDD | 3.5 | 28.0 | V |
| Operating temperature, | T _A | -40 | 125 | °C |
| Output current | IOUT | 0 | 350** | mA |

Notes: ** Using 25mm² FR4 Signal layer PCB (1 oz) under VM=9.0V test.



Electrical Characteristics

VM=12V, $T_A = 25^{\circ}C$, over recommended operating conditions (unless otherwise noted)

| | PARAMETER UNIT | TEST CONDITIONS | MIN | TYP | MAX | UNIT |
|------------------|-------------------------------------------|-------------------------------------------|-----|-----|------|-------|
| VDD | VDD operating voltage | | 3.5 | | 24.0 | V |
| I _{VDD} | VDD operating supply current | VM=12V | | 3.0 | 5.0 | mA |
| Rdson | High-side & Low-side FET on resistance | VM=12V, LS+HS, I _{OUT} =250mA | | 2.3 | | Ω |
| FG | FG Output Low Voltage | 5mA | | 0.3 | | V |
| BOP | Operating Point | | | 30 | | Gauss |
| B _{RP} | Releasing Point | | | -30 | | Gauss |
| T _{SD} | Thermal shutdown temperature | | | 150 | | °C |
| T _{HYS} | Thermal shutdown hysteresis | | | 40 | | |

Driver output vs. magnetic pole

| Characteristics | Test Conditions | DO | DOB |
|-----------------|-----------------|------|------|
| North pole | B < Brp | High | Low |
| South pole | B > Bop | Low | High |





Block Diagram



Application Notes:

1. Schematic Descriptions



Notes : C1>=1uF(Option), Enhance the reliability during hot swap.



Package SIP4





IMPORTANT NOTICE

Syta Technology Corporation (Sytatek) reserves the right to make corrections, modifications, enhancements, improvements, and other changes to its products and to discontinue any product without notice at any time.

Sytatek cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Sytatek product. No circuit patent licenses are implied.